



Professional Compact Colour LED Printer

Compact Design, Expertly Engineered

HL-L8240CDW



PRINT



WIRELESS

www.brother.com.au

Professional Compact Colour LED Printer

Combining professional performance with fast print speeds, minimal maintenance, and long-lasting supplies.

The compact, whisper-quiet HL-L8240CDW has been expertly engineered to meet the needs of your office with ease.

HL-L8240CDW



Key features:

- Fast print speeds of up to 30 pages per minute⁹
- Large paper capacity of 250 sheets, plus expandable up to 500 sheets with additional optional trays⁶
- Automatic 2-sided (duplex) printing
- Easy to use 6.8cm colour touchscreen
- Gigabit ethernet, 2.4GHz/5GHz Wi-Fi and USB 2.0 connectivity
- NFC for secure authentication
- Print directly from desktop, USB or mobile app
- 512MB internal memory
- Up to 2,600 black and 1,400 colour pages in-box toners¹¹
- Super high-yield replacement toners available, up to 4,500 black and 4,000 colour pages¹¹
- Available under a Managed Print Service (MPS) contract
- Compatible with Brother and 3rd Party solutions




Compact and expertly engineered

Designed by experts, our most compact, professional colour laser printer delivers high-quality outputs every time, allowing you to make the most of your office space. Every component has been optimised to reduce the overall size of the device without compromising on performance. With easy paper access and the ability to add an optional paper tray for additional flexibility, this device has been developed for high print volume to meet the needs of a busy office.



Make printing easy with Brother MPS

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to protect your data. The HL-L8240CDW provides a range of robust features including triple-layer security at a device, network and document level which is verified through external security certification. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.



Quiet without compromise

With its streamlined design, the HL-L8240CDW is engineered to print quietly whilst delivering speeds up to 25% faster than the previous generation, so you can print continuously without distraction and focus on your work.



Secure by design

Managed Print Services (MPS) supports you to get the best out of your devices - that's why the HL-L8240CDW has been designed with MPS in mind. Whatever your printing needs, we'll be at your side to find the solution that simplifies printer admin, saves time, keeps costs down, and helps you stay productive, by partnering with our national MPS partner network to deliver a service that's fit for your business.



Solutions ready

Automate workflows and improve business processes and security with print management solutions. A suite of security and workflow solutions can be added to the HL-L8240CDW to provide additional professional features to further improve your business processes.



Designed to go the distance

Built to perform for longer, the HL-L8240CDW has been designed with you in mind. Made from robust and hard-wearing materials and supported by outstanding service as standard, Brother's award-winning reliability allows you to deliver uncompromised performance at all times.



Seamless integration

As a Brother customer, you'll have access to a wide choice of leading software vendors, including PaperCut and YSoft, to create tailored solutions for your specific requirements that ensure your HL-L8240CDW works even harder to meet your needs.



Brother at your side support

Wherever you are in Australia, Brother offers [free product support](#) for the lifetime of your product.

| General | |
|---|---|
| Engine | Colour LED |
| Carton Contents | Printer, Quick Setup Guide, Users Guide, CD-ROM (Windows), Power Cord, CMYK Toner (TN258C/TN258M/TN258Y/TN258BK) Up to 1,000 pages ¹¹ |
| Display | |
| LED Display | Green x1 (Power) |
| LCD Display | 6.8cm Colour LCD (5.8cm Touchscreen) |
| Control Panel Switches | Power On/Off |
| Printer | |
| Standard Memory | 512MB |
| Print Speed ⁹ | Up to 30 ppm Mono / Up to 30 ppm Colour |
| 2 Sided Print Speed ⁹ | Up to 12/12ipm or 6/6ppm (Mono/Colour, based on ISO/IEC 24734) |
| 2 Sided Print | Yes (Automatic) |
| Emulation | PCL6, BR-Script3 |
| Printer Resolution | 600 x 600 dpi, 2400 dpi (2400 x 600) quality |
| First Print Out Time ¹⁰ | Less than 12.5 secs Mono/Colour (From Ready mode and standard tray) Less than 30 secs Mono/Colour (From Sleep mode and standard tray) |
| Warm Up Time | Less than 24 sec from Sleep, Less than 28 sec from Power On |
| Resident Barcodes | Code39, Interleaved 2 of 5, FIM(US-PostNet), Post Net(US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN(EAN), ISBN(UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI |
| Resident Fonts | PCL: 73 scalable fonts, 12 bitmap fonts, 16 bar codes PS: 66 scalable fonts |
| Quiet Mode | A mode to reduce the printing noise by reducing the print speed |
| Direct USB | Yes - Print |
| USB Host | Yes for External IC Card Reader (CH-1000) (Front) |
| Recommended Monthly Print Volume ⁸ | 1,000 to 4,000 pages |
| Direct Print Feature | |
| Digital-Media Spec | USB Memory Drive (Individual files no larger than 2GB) |
| Digital-Media Format | PDF version1.7, JPEG, Exif+JPEG, PRN (created by own printer driver), TIFF (MH, scanned by Brother model), XPS Version 1.0 |
| Connectivity | |
| Interface | Hi-Speed USB 2.0, 10Base-T/100Base-TX/1000Base-T Ethernet, 2.4/5Ghz Wi-Fi, NFC |
| USB Interface | Hi-Speed USB 2.0 |
| Wired Interface | 10Base-T/100Base-TX/1000Base-T Ethernet |
| Wireless Interface | 2.4GHz IEEE 802.11b/g/n, 5GHz IEEE 802.11a/n |
| Wi-Fi Direct | IEEE 802.11g/n (Wi-Fi Direct) |
| NFC | Yes |
| Wireless Mode | 2.4GHz IEEE 802.11b/g/n (Infrastructure Mode mode), 5GHz IEEE 802.11a/n (Infrastructure Mode mode) |
| Wireless Setup Support Utility | Wi-Fi Protected Setup (WPS) |
| Network Protocols IPV4 | ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMP, Web Services (Print), CIFS client, SNTTP client, LDAP, Syslog |
| Network Protocols IPV6 | NDP, RA, DNS resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMPv6, Web Services (Print), CIFS Client, SNTTP Client, LDAP, Syslog |

| Security | |
|---|--|
| Active Directory Authentication | Restrict the use of your Brother device. The device's control panel will be locked |
| LDAP | Integrate with a directory server to look up contacts and e-mail addresses |
| Wireless Security Protocols | WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), WPA3-SAE(AES), Wi-Fi Direct supports WPA2-PSK (AES) only |
| Wireless Certification | Wi-Fi Certification Mark License (WPA3 - Enterprise, Personal), Wi-Fi Protected Setup (WPS) Identifier Mark License, Wi-Fi CERTIFIED Wi-Fi Direct |
| IPv4-Filter | Restrict which network users can or cannot access the device over the network (IPv4 only) |
| Secure Function Lock | Version 3, 100 users |
| Network Management Utilities | |
| Network Management | Windows: BRAdmin Light, Web Base Management, BRAdmin Professional, Network Remote Setup Mac: Web Base Management, Network Remote Setup Linux: Web Base Management |
| Web Based Management | Web based print management software embedded onto the device |
| BRAdmin Professional ¹ | For LAN / WAN management using Windows® PC |
| Email Alerts | E-mail Notification and E-mail Reports |
| Store Print Log to Network | User level usage data recorded to either a text or csv file direct to a network folder |
| Mobile/Web Printing | |
| Mobile Connect ¹ | Use Brother Mobile Connect to print as well as manage your machine and customise its features. |
| Universal Print ⁷ | Yes with latest firmware |
| Web Connect ⁷ | Print from: Google Drive, Evernote, DropBox, Box, OneDrive, OneNote, SharePoint Online\ |
| AirPrint | Print most common file types from any Apple AirPrint enabled application |
| Mopria ¹ | Print most common file types from Mopria™ supported Android devices |
| Google ChromeOS | Print |
| Android Print Service Plugin ¹ | Print directly from your Android devices (Android 5.0 or later), to your Brother printer through a Wi-Fi or Wired network |
| Paper Handling ⁶ | |
| Standard Paper Capacity | Up to 250 Sheets |
| Multi-Purpose Tray Capacity | Up to 30 sheets / 3 Envelopes |
| Envelopes Input | Up to 3 envelopes face down (MP tray only) output via rear |
| Output Paper Capacity | Up to 150 Sheets Face Down (80gsm) 1 sheet face-up (straight paper path) |
| Media Weights Paper Tray | 60 - 163 gsm |
| Media Weights Paper Tray (Option) | 60 - 105 gsm |
| Media Weights Manual Feed Slot | 60 - 163 gsm |
| Media Weights Duplex | 60 - 105 gsm |
| Media Size Paper Tray | A4, Letter, Legal, Mexican Legal, India Legal, Executive, A5, A5 Long Edge, A6, B5(JIS), B5(SO), B6(JIS), A4 Short(270mm), Folio, 16K(195x270mm) |
| Media Size Paper Tray (Option) | A4, Letter, B5(JIS), A5, Executive, Legal, Mexico Legal, India Legal, A4 Short (270mm Paper), Folio, 16K(195x270mm) |
| Media Size Manual Feed Slot | Width 76.2 to 216 mm, Length 116 to 355.6 mm Envelope; COM-10, DL, C5, Monarch |
| Media Size Duplex | A4 |
| Media Types Paper Tray | Plain Paper, Thin Paper, Thick Paper, Recycled Paper |
| Media Types Paper Tray (Option) | Plain Paper, Thin Paper, Recycled Paper |
| Media Types Manual Feed Slot | Plain Paper, Thin Paper, Thick Paper, Recycled Paper, Bond, Label, Envelope, Envelope Thin, Envelope Thick, Glossy Paper |
| Media Types Duplex | Plain Paper, Thin Paper, Recycled Paper |

| Software | |
|---|---|
| Printer OS Compatibility ³ | Windows 11, Windows 10 (32&64bit), Windows Server 2022, Windows Server 2019, Windows Server 2016, Windows Server 2012 R2 (64-bit), Windows Server 2012 (64-bit) macOS 11 - 13 ³ Linux CUPS, LPD/LPRng (x86/x64 environment) |
| Software Available | Windows: iPrint&Scan ¹ , Status Monitor, BRAdmin Light ¹ , BRAdmin Professional ¹ , Driver Deployment Wizard ¹ Mac: iPrint&Scan ¹ , Status Monitor |
| Printer Driver Functions | Windows: Poster, N in 1, Header-Footer, Watermark, Duplex, Secure Print, Toner Save Mode Mac: N in 1, Duplex, Secure Print, Toner Save |
| N-up Printing ⁵ | Windows only |
| Poster Printing ⁴ | 1 in 2x2, 3x3, 4x4, 5x5 (Windows only) |
| Header and Footer Printing ⁴ | Windows only |
| Watermark Printing ⁴ | Windows only |
| Secure Print ⁵ | Use Secure Print to ensure that confidential or sensitive documents do not print until you enter a password on the machine's control panel. (Windows/Mac) |
| Brother Solutions Interface | Brother Solutions Interface (BSI) Developer Program is a platform that enables third-party developers to build custom solutions for and integrate with Brother Devices |
| Mass Deployment Tool ¹ | A configuration tool to help you to install and manage multiple USB-connected or network-connected devices without having to install any additional software |
| Driver Deployment Wizard ¹ | A quick & easy way to deploy Brother printer drivers on a networked Windows [®] PC |
| Carbon Copy | Yes |
| Light Solutions | ThinPrint Client, Barcode Print+ (Apply for Activation Code from Brother) |
| iPrint&Scan ¹ | Windows/Mac (Print Only) |
| Options | |
| Optional Warranty ¹⁴ | 1 or 2 or 3 Years On-Site |
| Optional Paper Tray | 250 sheets (LT-310CL) x 1 |

| Environment | |
|--------------------------------------|--|
| Power Consumption | Peak: Average 960W, Ready: Average 65W, Sleep: 9.1W, Deep Sleep: 0.45W, Power Off: 0.04W |
| Sleep Mode | 0-50 min |
| Toner Save | This reduces the toner usage and helps to reduce the total cost of printer ownership |
| Power Save | This enables the printer to consume less energy when not in use |
| Temperature | Operating: 10 - 32°C, Storage: 0 - 40°C |
| Humidity | Operating: 20 - 80%, Storage: 35 - 85% |
| Consumables | |
| Consumables ¹¹ | Belt Unit: Up to 60,000 pages (3-page per job) (BU229CL) Waste Toner Box: Up to 50,000 pages (WT229CL) Drum Unit: Up to 20,000 pages (1-page per job) (DR258CL) |
| Inbox Consumables ¹¹ | Colour Toner Yield Up to 1,400 pages ¹¹ Black Toner Yield Up to 2,600 pages ¹¹ |
| Standard Yield Toner ¹¹ | CMYK Toner Standard Yield (TN258C/TN258M/TN258Y/TN258BK) Up to 1,000 pages ¹¹ |
| High Yield Toner ¹¹ | Black Toner High Yield (TN258XLBK) Up to 3,000 pages Colour Toner High Yield (TN258XLC/TN258XLM/TN258XLY) Up to 2,300 pages |
| Super High Yield Toner ¹¹ | Black Toner Super High Yield (TN259BK) Up to 4,500 pages ¹¹ Colour Toner Super High Yield (TN259C/TN259M/TN259Y) Up to 4,000 pages ¹¹ |
| Weights & Measurements | |
| Size | 399(W) x 446(D) x 274(H)mm |
| Weight | 12.6 Kg without consumables 16.6 Kg with consumables |
| Size With Carton | 488(W) x 535(D) x 370(H)mm |
| Weight With Carton | 19.6 Kg with consumables |
| Others | |
| Noise Level | Sound Pressure Level: (Printing) Less than 48 dBA, (Ready) InAudible Sound Power Level: (Printing) Less than 6.50 B(A), (Ready) InAudible |
| TEC Value | 0.47 kWh/Week |

1. Download from Brother Solutions Centre
2. Apply to activate
3. Via Airprint or iPrint&Scan
4. Windows only
5. Windows/Mac
6. Capacity calculated with 80g/m² paper
7. Must be connected to the internet
8. The recommended monthly print volume is to achieve the best possible performance and printer life
9. Print speeds based on ISO/IEC 24734 (www.brother.com/rd/printspeed)
10. FPOT (First Print Out Time) based on ISO/IEC 17629
11. Approx. declared yield value in accordance with ISO/IEC 19798
13. Purchase optional tray required
14. Purchase optional onsite warranty required

All specifications correct at time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com



brother
at your side