



Compact 4-in-1 Monochrome Laser Printer

MFC-L2710DW











PRINT

COPY

SCAN

ΕΔ¥

WIRELESS

Compact 4-in-1 Monochrome Laser Printer

The MFC-L2710DW is ideal for the busy home and small office. This simple to use and easy to setup device, provides professional quality prints, together with built-in wired and wireless connectivity for printing from mobile phones and tablets.

MFC-L2710DW



Key Features:

- Fast print speeds of up to 30 ppm
- Automatic (duplex) print
- 250 sheet paper input
- 50 sheet Automatic Document Feeder
- Built-in wired and wireless connectivity
- Up to 3,000 page optional high-yield toner
- 64MB memory



Business performance

Successor to the BLI Pick Award winning 'MFC-L2700DW', the MFC-L2710DW is designed to be set-up and ready to be used in minutes. Compact and desktop friendly, you can enjoy fast print speeds of up to 30 ppm, and a large 50 sheet Automatic Document Feeder for multi-page copying and scanning. Easily share documents by scanning and sending directly via email, or save to SharePoint (local infrastructure only) and other destinations.

Maximum value for money

The wireless MFC-L2710DW comes with a host of cost saving elements including automatic 2-sided (duplex) printing, and high-yield toner cartridges reduces the cost of each print job.

Quiet without compromise

Print quietly without comprising on speed or quality, operating at the lowest decibel in class (under 50dB). This desktop friendly printer, can sit on your desk, printing quietly at full speed in the background, while you work.

Designed to go the distance

Built to perform for longer, the MFC-L2710DW has been designed with you in mind. Made from robust and hardwearing materials and supported by outstanding service as standard, Brother's award winning** reliability allows you to deliver uncompromised performance at all times.



General		Mobile/Web Based Printing	& Scanning
Technology	Electro-photographic Laser Printer	Brother iPrint&Scan (Android)	Print from, scan to, send faxes, preview received faxes preview copies and check the machine status from an
Laser Classification	Class 1 Laser Product (IEC60825-1:2014)		Android device
Processor	600MHz	Brother iPrint&Scan	Print from, scan to, send faxes, preview received faxes
Memory	64MB	(iPad / iPhone / iPod)	preview copies and check the machine status from an iPad / iPhone / iPod Touch
Wired Network Interface	0Base-T/100Base-TX	Brother iPrint&Scan	Print from and scan to a smart phone running the
Wireless Network	IEEE 802.11b/g/n	(Windows® Phone)	Windows® Phone Operating System
Control Panel Local Interface	2 Line, 16 character LCD Display Hi-Speed USB 2.0	Brother iPrint&Scan (Windows® 8,10 & RT)	Print from and scan to a Windows® 8,10 or Windows RT Tablet
Print		AirPrint	Print from and scan to most common file types from any AirPrint enabled application
Print Speed Standard (A4)	Up to 30 ppm (pages per minute)	Brother Print Service Plugin	Print from Android devices without a dedicated App
Print Speed 2-sided (duplex) (A4)	Up to 15 sides per minute (8 sheets per minute)	Mopria	Print most common file types from Mopria supported
Resolution	Up to 1,200 x 1,200dpi		Android devices
Quiet Mode	A mode to reduce the printing noise by reducing the	Сору	
	print speed to 13ppm	Speed - (A4)	Up to 30cpm (copies per minute)
Automatic 2-sided (duplex) Printing	Print on to both sides of the paper	FCOT (First Copy Time Out)	Less than 10 seconds from ready mode
FPOT (First Print Out Time)	Less than 8.5 seconds from ready mode	Resolution	Up to 600 x 600dpi
Warm Up Time	Less than 9 seconds from	Multi-Copying/Stack/Sort	Makes up to 99 copies of each page / Stacks or Sorts
Print Languages	sleep mode GDI	Enlargement/Reduction Ratio	Reduce or Increase document sizes from 25% to 400% in 1% increments
Printer Functions		N in 1 Copying	Allows the user to compress 2 or 4 pages on to a single A4 sheet
N-up Printing ³	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)	2in1 ID Copying	Allows the user to copy both sides of an ID card to a single A4 sheet
Poster Printing ⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25	Grey Scale	256 shades of grey (8 bit)
Watermark Printing ⁴	A4 pages Watermark your documents with predefined text or with	Receipt Copying	Produces clearer copies of receipts
	your own user-defined messages	Scan	
ID Printing ⁴	Add identification to your printed documents (date & time, short custom message or PC username)	Scanner Type	CIS (Contact Image Sensor)
Manual 2-sided (duplex) Print ⁴	Manual 2-sided printing (recommended for media not	Colour & Mono Scanning	Yes
Manaar 2 oldod (daploxy i iiit	supported by automatic 2-sided print)	Scan Speed Monochrome	23.6 ipm (images per minute)
Booklet Printing ⁴	Print documents in A5	Scan Speed Colour	7.5 ipm (images per minute)
D D. #1. 2	booklet format using automatic or manual 2-sided print	Scan Resolution from ADF	Up to 600 x 600dpi
Print Profiles ³	Store your favourite driver settings as profiles to easily recall them	Scan Resolution from Scanner Glass	Up to 1,200 x 1,200dpi
Print Text In Black ⁴	Converts all text in your documents to black when	Interpolated Scan Resolution	Up to 19,200 x 19,200dpi
	printed	Colour Depth	16,777,216 colour variations (24 bit)
Print Archive ⁴	An electronic carbon copy feature that saves an electronic copy of all printed documents as a PDF file	Grey Scale	256 shades of grey (8 bit)
	electronic copy of all printed documents as a PDF life	Standard Functions ⁷	Scan to E-mail, OCR, Image & File
Printer Driver Windows®	Windows 11®, Windows® 10 (32&64bit), Windows®	Scan Features	Remove Background, Skip Blank Page ⁴ , ID Scan ⁴ , 1 to 2 Scan ⁴ , Split PDF
WIIIUUWS	8/8.1 (32&64bit), Windows® 7 (32&64bit), Windows® Server 2019, Windows® Server 2016, Windows®	Scan to SharePoint (Local infrastructure only)	Scan documents directly into SharePoint
	Server 2012/R2 (64bit), Windows® Server 2008 (32&64bit), Windows® Server 2008 R2	Windows® Web Services Scanning	Scan direct into Windows® (from Windows® 7 & onwards) without needing to install a scanner driver
Macintosh ⁵	Mac OSX 10.10.5 or greater	Coopper Driver	,
Linux ⁵	CUPS, LPD/LPRng (32 & 64 bit editions)	Scanner Driver Windows®	TWAIN & WIA, Windows 11®, Windows® 10 (32 &
Standard Paper Handling		windows	64 bit editions), Windows® 8.1 (32 & 64 bit editions),
Paper Input ²	Standard Tray - 250 sheets, Manual Feed Slot - 1 sheet		Windows® 8 (32 & 64 bit editions), Windows® 7 (32 & 64 bit editions)
Automatic Document Feeder (ADF)	50 sheets	Macintosh ⁵	TWAIN & AirPrint 10.10.5 or greater
Paper Output ²	Face Down - 120 sheets Face Up (Straight Paper Path) - 1 sheet	Linux ⁵	SANE (32 & 64 bit editions)
Madia Cacaifications		Fleet Management Tools	
Media Specifications Modia Types & Weights Standard	Plain & recycled paper (behaves 50 1602/mg)	Unattended Installer ⁴	TWAIN & WIA, Windows® 7, Windows® 8, Windows® 10, Windows® 11
Media Types & Weights Standard Manual feed slot	Plain & recycled paper (between 60 - 163g/m2) Plain, Recycled, Bond, Label, Envelope (between 60	MSI Installer⁴	Mac OS X 10.14.6 - 10.15, macOS 11
O sided (dueles) Dire	- 230g/m2)	BRAdmin Light ⁴⁸⁵	LAN/WAN management software
2-sided (duplex) Print	Plain & recycled paper (between 60 - 105g/m2)	Embedded Web Server	Web based print management software embedded
Envelope & Label Printing	Yes, from the Manual feel slot: support for 1 envelope / sheet		onto the device
Media Sizes Standard Tray	A4, Letter, A5, A5 (Long Edge), A6, Executive	Driver Deployment Wizard ⁴	Easily create print drivers for hassle free deployment over your network
Manual feed slot	Width: 76.2mm to 215.9mm x Length: 127mm to 355.6mm		order your notificity
2-sided (duplex) Print	A4		

Address Book	
Speed Dials	200 locations for E-mail addresses and fax numbers
Group Dial	A combination of up to 20 groups can be stored for broadcasting
Network and Security	
Wired Network	Built in Ethernet 10Base-T/100Base-TX
Network Protocols	TCP/IP (IPv4 and IPv6)
Wired Network Security	SMTP-AUTH, SNMP v3,SSL/TLS(SMTP,HTTP,IPP)
Wireless Network	IEEE 802.11b/g/n (Infrastructure Mode / Adhoc Mode)
Wireless Set-Up Support	Wi-Fi Protected Setup (WPS)
Wireless Applications	Vertical Pairing
IPv4	ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port Port9100, SMTP Client, IPP/IPPS, FTP Server, SNMPV1/V2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print), SNTP Client
IPv6	NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTP Client, Web Services (Print)
E-mail Notifications	Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing
E-mail Reports	Receive usage reports on a regular basis via e-mail
IP Filter	Restrict which network users can or cannot access the device over the network (IPv4 only)
Setting Lock	Secures access to the devices control panel by locking it
Supplies	
In-box Toner	700 pages ¹
Standard Yield Toner	1,200 pages ¹ (TN-2430)
High Yield Toner	3,000 pages ¹ (TN-2450)
Drum (DR-2424)	Approx 12,000 pages
Carton Contents	Toner cartridge, drum, power supply cord, driver software for Windows®, Quick Set-Up Guide (PC interface cable NOT included) The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.
Dimensions and Weights	
With Carton (WxDxH) Without Carton (WxDxH)	410 x 398.5 x 318.5 mm - 11.8kg 580 x 517 x 434 mm - 14.7kg
Duty Cycles	
Recommended Monthly	Up to 2,000 pages monthly print volume
Environment	
Power Consumption	Printing - 440W (260W in quiet mode), Ready - 42W, Sleep - 6.2W, Deep sleep - 0.6W, Off - 0.03W
Sound Pressure Level	Printing - 48dbA, Quiet mode printing - 44dbA, Ready - Up to 30dbA
Power Saving	This enables the printer to consume less energy when not in use
Toner Saving	This reduces the toner usage and helps to reduce the total cost of printer ownership
Eco Mode	Yes

гах	
Fax Modem	33,600bps (Super G3)
PC Fax Send ^{9&3}	Send faxes directly from your PC
PC Fax Receive ^{9&4}	Receive faxes directly to your PC
Automatic Redial	Automatic redialling if the recipient fax is busy
Telephone Index	An electronic, alphabetical listing of stored speed dials and group numbers
Chain Dialling	Allows the user to store parts for long dialling sequences in different speed dial locations
Speaker/Ring Volume	3 levels and off
Fax/Telephone Switch	Automatic recognition of fax and telephone reception
Super Fine	Enables quality transmission of very small print and line drawings
Contrast	Auto / light / dark
Enhanced Remote Activate	Transfer a fax call, answered on an extension phone, to the fax machine
Delayed Timer	Up to 50
Quick-Scan	Approximately 2.5 seconds per page A4 standard resolution
Memory Transmission	Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Out of Paper Reception	Up to 400 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Dual Access	Send the same fax message to up to 250 separate locations (manual 50 locations)
Broadcasting	Receive usage reports on a regular basis via e-mail
Auto Reduction	When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet
ECM (Error Correction Mode)	The MFC will detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)
Fax Forwarding	Sends a fax received in memory to another pre- programmed fax number
Remote Access	Allows users to remotely access their machine
Fax Retrieval	Allows remote access to faxes stored in the machine
Remote Maintenance	Allows users to maintain their MFC remotely
Remote Set-up ³	Allows users to set-up the MFC from their PC
Grey Scale	256 shades (8 bit) of grey are available for faxing
Fax Stamp	Add the date and time to all received faxes
Cover Page	Create custom cover pages for outgoing faxes

- 1 Approx declared yield value in accordance with ISO/IEC 19752.
- 2 Calculated with 80g/m² paper.
- 3 Windows® & Mac® only. 4 Windows® only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.
 - For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.
- 7 Requires Brother software.

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.









www.brotherearth.com

