



Compact 4-in-1 Monochrome Laser Printer

MFC-L2750DW



PRINT



COPY



SCAN



FAX



WIRELESS

Compact 4-in-1 Monochrome Laser Printer

The MFC-L2750DW is ideal for the busy home and small office, requiring multifunction capabilities. This quiet, compact, desktop printer boasts wired and wireless connectivity, large Automatic Document Feeder supporting automatic 2-sided (duplex) scan and copy functionality and 250 sheet paper tray. The addition of NFC (Near-Field Communication) provides the convenience of 'Tap and print' from mobile devices.

MFC-L2750DW



Key Features:

- Fast print speeds of up to 34 ppm
- Automatic 2-sided (duplex) print, scan and copy
- 250 sheet paper input
- 50 sheet Automatic Document Feeder
- Built-in wired and wireless connectivity
- Near-Field Communication (NFC), for mobile print
- Up to 3,000 page option high-yield toner
- 6.8cm colour touchscreen
- 256MB memory

Business performance

Successor to the BLI Pick Award winning 'MFC-L2740DW', the MFC-L2750DW is engineered to increase efficiency, with fast print speeds of up to 34 ppm with automatic 2-sided (duplex) print, and 50 sheet Automatic Document Feeder for automatic (duplex) copy and scan. Save time by using the print-from and scan-to popular cloud services directly from the 6.8cm touchscreen, including Dropbox, Google Drive™, Evernote, OneNote and more. Enjoy the added benefit of creating up to 12 custom shortcuts on the touchscreen for your most used features. Together with built-in NFC, you can now use your mobile phone and 'touch' to print for added ease of use.

Maximum value for money

More pages can be printed with the up to 3,000 page optional high-yield toner, ensuring that you are ready to print, again and again. Together with a host of feature rich functionality, high-precision laser technology ensures that your print outs are professional and cost effective.

Quiet without compromise

Print quietly without compromising on speed or quality, operating at the lowest decibel in class (under 50dB). All the models throughout the range are designed to sit on your desk, printing quietly at full speed while you work without interruption.

Designed to go the distance

Built to perform for longer, the MFC-L2750DW has been designed with you in mind. Made from robust and hardwearing materials and supported by outstanding service as standard, Brother's award winning** reliability allows you to deliver uncompromised performance at all times.

brother
at your side

General	
Technology	Electrophotographic Laser Printer
Laser Classification	Class 1 Laser Product (IEC60825-1:2014)
Processor	600MHz
Memory	256MB
Wired Network Interface	10Base-T/100Base-TX
Wireless Network	IEEE 802.11b/g/n
Control Panel	6.8cm colour touchscreen
Local Interface	Hi-Speed USB 2.0
Shortcuts	12
Print	
Print Speed Standard (A4)	Up to 34 ppm (pages per minute)
Print Speed 2-sided (duplex) (A4)	Up to 16 sides per minute (8 sheets per minute)
Automatic 2-sided (duplex) Printing	Print on to both sides of the paper
Resolution	Up to 1,200 x 1,200 dpi
Quiet Mode	A mode to reduce the printing noise by reducing the print speed to 13 ppm
FPOT (First Print Out Time)	Less than 8.5 seconds from ready mode
Warm Up Time	Less than 9 seconds from sleep mode
Print Languages	PCL6, BR-Script ³ (PostScript ³ ™ Language Emulation), PDF version 1.7
Embedded Fonts (PCL)	66 scalable fonts, 12 bitmap fonts, 16 barcodes
Embedded Fonts (Postscript)	66 scalable fonts
Embedded Barcodes (PCL)	Code39, Interleaved 2 of 5, FIM (US-PostNet, Post Net (US-PostNet) EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN(EAN), ISBN(UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI
Printer Functions	
N-up Printing³	Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)
Poster Printing⁴	Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages
Watermark Printing⁴	Watermark your documents with predefined text or with your own user-defined messages
ID Printing⁴	Add identification to your printed documents (date & time, short custom message or PC username)
Manual 2-sided (duplex) Print⁴	Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)
Booklet Printing⁴	Print documents in A5 booklet format using automatic or manual 2-sided print
Print Profiles⁵	Store your favourite driver settings as profiles to easily recall them
Print Text In Black⁴	Converts all text in your documents to black when printed
Print Archive⁵	An electronic carbon copy feature that saves an electronic copy of all printed documents as a PDF file
Printer Driver	
Windows[®]	Windows 11 [®] , Windows [®] 10 (32&64bit), Windows [®] 8/8.1 (32&64bit), Windows [®] 7 (32&64bit), Windows [®] Server 2019, Windows [®] Server 2016, Windows [®] Server 2012/R2 (64bit), Windows [®] Server 2008 (32&64bit), Windows [®] Server 2008 R2
Macintosh⁵	Mac OSX 10.10.5 or greater
Linux⁵	CUPS, LPD/LPRng (32 & 64 bit editions)
PostScript Universal Printer Driver	Driver for Windows [®] that enables you to print to any network or locally-connected Brother laser printer that supports PostScript
PCL Driver	Generic PCL XL driver
Standard Paper Handling	
Paper Input²	Standard Tray - 250 sheets Manual feed slot - 1 sheet
Automatic Document Feeder (ADF)	50 sheets
Paper Output²	Face Down - 120 sheets Face Up (Straight Paper Path) - 1 sheet
Media Specification	
Media Types & Weights	Standard Tray – Plain & recycled paper (between 60 - 163g/m ²) Manual Feed Slot – Plain, Recycled, Bond, Label, Envelope, (between 60 - 230g/m ²) 2-sided (duplex) Print – Plain & recycled paper (between 60 - 105g/m ²)
Envelope Printing	Yes, from the Manual feed slot: support for 1 envelope / sheet
Media Sizes	Standard Tray – A4, Letter, A5, A5 (Long Edge), A6, Executive Manual Feed Slot – Width: 76.2mm to 215.9mm x Length: 127mm to 355.6mm 2-sided (duplex) Print – A4

Mobile / Web Based Printing & Scanning	
Brother iPrint&Scan (Android)	Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device
Brother iPrint&Scan (iPad / iPhone / iPod)	Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an iPad / iPhone / iPod Touch.
Brother iPrint&Scan (Windows[®] Phone)	Print from and scan to a smart phone running the Windows [®] Phone Operating System
Brother Print&Scan (Windows[®] 8, 10 & RT)	Print from and scan to a Windows [®] 8, 10 or Windows RT Tablet
CreativeCentre⁵	Download and print Brother CreativeCenter content
AirPrint	Print from and scan to most common file types from any AirPrint enabled application
Mopria	Print most common file types from Mopria supported Android devices
Brother Print Service Plugin	Print from Android devices without a dedicated App
Web Connect⁸	Print from and scan to without using a PC on Box, Dropbox, Evernote, OneDrive, Google Drive™ OneNote
Copy	
Speed – (A4)	Up to 34 cpm (copies per minute)
FCOT (First Copy Out Time)	Less than 10 seconds from ready mode
Resolution	Up to 600 x 600 dpi
Multi-Copying / Stack / Sort	Makes up to 99 copies of each page / Stacks or Sorts
Enlargement / Reduction Ratio	Reduce or Increase document sizes from 25% to 400% in 1% increments
N in 1 Copying	Allows the user to compress 2 or 4 pages on to a single A4 sheet
2in1 ID Copying	Allows the user to copy both sides of an ID card to a single A4 sheet
Grey Scale	256 shades of grey (8 bit)
Receipt Copying	Produces clearer copies of receipts
Enlarge Text Copy⁹	Makes reading copied documents easier if the size of the text on the original document is small
Scan	
Scanner Type	CIS (Contact Image Sensor)
Colour & Monochrome Scanning	Yes
Scan Speed Monochrome	23.6 ipm (images per minute)
Scan Speed Colour	7.5 ipm (images per minute)
Scan Resolution from ADF	Up to 600 x 600dpi
Scan Resolution from Scanner Glass	Up to 1,200 x 1,200dpi
Interpolated Scan Resolution	Up to 19,200 x 19,200dpi
Colour Depth	16, 777, 216 colour variations (24 bit)
Grey Scale	256 shades of grey (8 bit)
Standard Functions⁹	Scan to E-mail, OCR, Image, File, FTP & Network. Cloud Scanning
Scan Features	Remove Background, Skip Blank Page4, ID Scan4, 1 to 2 Scan4, Split PDF
Scan to Microsoft Office⁶	Scan to Microsoft [®] Word, Microsoft [®] Excel & Microsoft [®] PowerPoint
Scan to Searchable PDF	Scan documents to searchable PDF files
Scan to Sharepoint (Local infrastructure only)	Scan documents directly into SharePoint
Windows[®] Web Services Scanning	Scan direct into Windows [®] (from Windows [®] 7 & onwards) without needing to install a scanner driver
Scanner Driver	
Windows[®]	TWAIN, WIA Windows 11 [®] , Windows [®] 10 (32 & 64 bit editions), Windows [®] 8 (32 & 64 bit editions), Windows [®] 8.1 (32 & 64 bit editions), Windows [®] 7 (32 & 64 bit editions),
Macintosh⁵	TWAIN & AirPrint macOS 10.10.5 or greater
Linux⁵	SANE(32 & 64 bit editions)

Fleet Management Tools	
Unattended Installer ¹	Ability to centrally deploy and customise our drivers and software
MSI Installer ⁴	Modular installers that can be distributed through Active Directory [®]
Embedded Web Server	Web based print management software embedded onto the device
BRAdmin Light ^{4&5}	LAN/WAN management software
Driver Deployment Wizard ⁴	Easily create print drivers for hassle free deployment over your network
Address Book	
Speed Dials	200 locations for E-mail addresses and fax numbers
Group Dial	A combination of up to 20 groups can be stored for broadcasting
Network & Security	
Wired Network	Built in Ethernet 10Base-T/100Base-TX
Network Protocols	TCP/IP (IPv4 and IPv6)
Wired Network Security	SMTP-AUTH, SNMP v3,SSL/TLS(SMTP,HTTP,IPP)
Wireless Network	IEEE 802.11b/g/n (Infrastructure Mode / Adhoc Mode)
Wireless Setup Support	Wi-Fi Protected Setup (WPS)
Wireless Applications	Vertical Pairing
IPv4	ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/PPS, FTP Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print), SNTIP Client
IPv6	NDP, RA, DNS resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/PPS, SMTP Client, FTP Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, SNTIP Client, Web Services (Print)
E-mail Notifications	Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing
E-mail Reports	Receive usage reports on a regular basis via e-mail
IP Filter	Restrict which network users can or cannot access the device over the network (IPv4 only)
Setting Lock	Secures access to the devices control panel by locking it
Supplies	
Inbox Toner	700 pages ¹
Standard Yield Toner	1,200 pages ¹ (TN-2430)
High Yield Toner	3,000 pages ¹ (TN-2450)
Drum (DR-2425)	Approx 12,000 pages
Carton Contents	Toner cartridge, drum, power supply cord, driver software for Windows [®] , Quick Set-Up Guide (PC interface cable NOT included) The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.
Dimensions & Weight	
With Carton (WxDxH)	580(W) x 517(D) x 434(H) mm - 14.9kg
Without Carton (WxDxH)	410(W) x 399(D) x 318(H) mm - 11.1kg (without consumables)
Duty Cycles	
Recommended Monthly	Up to 2,000 pages monthly print volume
Environment	
Power Consumption	Printing - 440W (260W in quiet mode), Ready - 42W, Sleep - 6.2W, Deep sleep - 0.6W, Off - 0.03W
Sound Pressure Level	Printing - 49dbA, Quiet mode printing - 44dbA, Ready - Up to 30dbA
Power Saving	This enables the printer to consume less energy when not in use
Toner Saving	This reduces the toner usage and helps to reduce the total cost of printer ownership
Eco Mode	Yes

Fax	
Fax Modem	33,600bps (Super G3)
PC Fax Send ^{8&3}	Send faxes directly from your PC
PC Fax Receive ^{8&4}	Receive faxes directly to your PC
Automatic Redial	Automatic redialling if the recipient fax is busy
Telephone Index	An electronic, alphabetical listing of stored speed dials and group numbers
Chain Dialing	Allows the user to store parts for long dialling sequences in different speed dial locations
Speaker / Ring volume	3 levels and off
Fax / Tel Switch	Automatic recognition of fax and telephone reception
Super Fine	Enables quality transmission of very small print and line drawings
Contrast	Auto / light / dark
Enhanced Remote Activate	Transfer a fax call, answered on an extension phone, to the fax machine
Delayed Timer	Up to 50
Quick-Scan	Approximately 2.5 seconds per page A4 standard resolution
Memory Transmission	Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Out of Paper Reception	Up to 500 pages (ITU-T Test Chart, Standard Resolution, JBIG)
Dual Access	Send the same fax message to up to 250 separate locations (manual 50 locations)
Broadcasting	Receive usage reports on a regular basis via e-mail
Auto Reduction	When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet
ECM (Error Correction Mode)	The MFC will detect line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)
Fax Forwarding	Sends a fax received in memory to another pre-programmed fax number
Remote Access	Allows users to remotely access their machine
Fax Retrieval	Allows remote access to faxes stored in the machine
Remote Maintenance	Allows users to maintain their MFC remotely
Remote Set-up ³	Allows users to set-up the MFC from their PC
Grey Scale	256 shades (8 bit) of grey are available for faxing
Fax Stamp	Add the date and time to all received faxes
Cover Page	Create custom cover pages for outgoing faxes

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

- 1 Approx declared yield value in accordance with ISO/IEC 19752.
- 2 Calculated with 80g/m² paper.
- 3 Windows[®] & Mac[®] only.
- 4 Windows[®] only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products.
For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.
- 7 Requires Brother Software.
- 8 Must be web connected.



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com



brother
at your side